

Default settings shaded.

Main menu	Sub menu	Display	Function		
SET ADDRESS	A001 ~ A508		DMX address setting		
USER MODE	Channel Mode: 05 / 06 / 07		DMX channel mode		
FUNCTION	Status	No DMX status	Close/Hold	Modes if no DMX	
	Fixture ID	Service PIN	Password=XXX	Passwort „050“	
		RDM PID	XXXXXX		
	Dimmer Curve	Linear	The increase in light intensity appears to be linear as DMX value is increased		
		Square	Light intensity control is finer at low levels and coarser at high levels		
		INV. Square	Light intensity control is coarser at low levels and finer at high levels		
		S-Curve	Light intensity control is fine at low levels and high levels and coarser at medium levels		
	Lamp Behavior	LED			
		Halogen			
	LCD. Set	Backlight	05M ~ 60M	Display shutoff time	
		Key lock	ON/OFF	Key lock activation	
		DispFlash	ON/OFF	Setting that the device will flash when there is no DMX signal received	
	Load	ON/OFF		Restore factory settings	
	Temp. C/F	Celsius		Select temperature designation °C or °F	
Fahrenheit					
INFORMATION	Time. Info	Current	XXXX (h)	Power on running time	
		Total time	XXXX (h)	Fixture running time	
		Last clear	XXXX (h)	Individual fixture running time	
		Timer PIN	Password=„050“		
	Temp. Info	XXX °C/°F		Inside temperature	
	Model. Info	LED THA-60PC		Model name	
	Software version	V 0.03		Software version	
TEST	Panel. Ctrl.	Dimmer = 000-255		Manual adjustment	
	Panel. Ctrl.	Strobe = 000-255		Manual adjustment	
	Program	Static	R/G/B/RG/GB/RB/RGB/BLAC F: 00 - 99		Manual adjustment
		Change	SP: 01 - 99 F: 00 - 99		Manual adjustment
		Fade	SP: 01 - 99 F: 00 - 99		Manual adjustment
		Auto	SP: 01 - 99 F: 00 - 99		Manual adjustment
	Sound	Sense	00 - 31		Manual adjustment