

## 8. DMX512 Operate

The product has 16 operate channels(international standard DMX512 signal),The details as follow:

Channel		DMX512 Value	Function
1	Dimmer	0~255	100 Grades
2	Strobe	0~1	No change
		2~255	speed from slow to fast
3	Pattern Groups	0~31	1st Group
		32~63	2nd Group
		64~95	3rd Group
		96~127	4th Group
		128~159	5th Group
		160~191	6th Group
		192~223	7th Group
		224~255	8th Group
4	Pattern	0~255	$258/8=32$ patterns
5	X rolling	0~255	from slow to fast
6	Y rolling	0~255	from slow to fast
7	Z rolling	0~255	from slow to fast
8	X move	0~255	from slow to fast
9	Y move	0~255	from slow to fast
10	X stretch	0~255	from slow to fast
11	Y stretch	0~255	from slow to fast
12	Zoom	0~255	from slow to fast
13	Slow-Drawing	0~255	from slow to fast
14	Dotting	0~255	from slow to fast
15	Scan speed	0~255	from slow to fast
16	Pattern Size	0~1	Original size
		2~255	100 Grades