

<b>Fog Fury Jett Pro</b>		<b>1 Channel Mode</b>
<b>Channel</b>	<b>Value</b>	<b>Function</b>
1	0 - 31 32 - 255	FOG & RANDOM COLOR CHANGE OFF MAX FOG & COLOR CHANGE

<b>Fog Fury Jett Pro</b>		<b>2 Channel Mode</b>
<b>Channel</b>	<b>Value</b>	<b>Function</b>
1	0 - 31 32 - 255	FOG OFF MAXIMUM FOG
2	0 - 255	COLOR MACROS Please see page 15 for Color Macros

<b>Fog Fury Jett Pro</b>		<b>3 Channel Mode</b>
<b>Channel</b>	<b>Value</b>	<b>Function</b>
1	0 - 31 32 - 255	FOG OFF MAX FOG
2	0 - 255	COLOR MACROS Please see page 15 for Color Macros
3	0 - 31 32 - 95 96 - 159 160 - 255	STROBING OFF STROBING SLOW - FAST PULSE EFFECT RANDOM STROBE SLOW - FAST

<b>Fog Fury Jett Pro</b>		<b>7 Channel Mode</b>
<b>Channel</b>	<b>Value</b>	<b>Function</b>
1	0 - 31 32 - 255	FOG OFF MAX FOG
2	0 - 255	RED 0% - 100%
3	0 - 255	GREEN 1 (OUTER LEDS) 0% - 100%
4	0 - 255	BLUE 0% - 100%
5	0 - 255	AMBER 0% - 100%
6	0 - 255	GREEN 2 (INNER LEDS) 0% - 100%
7	0 - 255	UV 0% - 100%

<b>Fog Fury Jett Pro</b>		<b>9 Channel Mode</b>
<b>Channel</b>	<b>Value</b>	<b>Function</b>
1	0 - 31 32 - 255	FOG OFF MAX FOG
2	0 - 255	RED 0% - 100%
3	0 - 255	GREEN 1 (OUTER LEDS) 0% - 100%
4	0 - 255	BLUE 0% - 100%
5	0 - 255	AMBER 0% - 100%
6	0 - 255	GREEN 2 (INNER LEDS) 0% - 100%
7	0 - 255	UV 0% - 100%
8	0 - 31 32 - 95 96 - 159 160 - 255	STROBING OFF STROBING SLOW - FAST PULSE EFFECT RANDOM STROBE SLOW - FAST
9	0 - 255	MASTER DIMMER 0% - 100%