

| Fusion FX Bar 5 DMX Channels & Functions | | |
|--|---|---|
| Channel | Value | Function |
| 1 | 0 - 7 8 - 190 191 - 200 201 - 247 248 - 255 | WHITE DIMMER/STROBE OFF MASTER DIMMER 0% - 100% SOUND ACTIVE STROBING SLOW - FAST FULL ON |
| 2 | 0 - 7 8 - 190 191 - 200 201 - 247 248 - 255 | MOON FLOWER DIMMER/STROBE OFF MASTER DIMMER 0% - 100% SOUND ACTIVE STROBING SLOW - FAST FULL ON |
| 3 | 0 - 18 19 - 37 38 - 56 57 - 75 76 - 94 95 - 113 114 - 127 128 - 159 160 - 191 192 - 223 224 - 255 | MOON FLOWER COLOR RED RED & GREEN GREEN GREEN & BLUE BLUE RED & BLUE RED, GREEN, & BLUE RED - GREEN GREEN - BLUE RED - BLUE RED - GREEN - BLUE |
| 4 | 0 - 9 10 - 120 121 - 134 135 - 245 246 - 255 | MOON FLOWER ROTATION NO ROTATION CLOCKWISE ROTATION FAST - SLOW NO ROTATION COUNTER CLOCKWISE ROTATION SLOW - FAST NO ROTATION |

| Fusion FX Bar 5 DMX Values and Functions | | |
|--|--|--|
| Channel | Value | Function |
| 5 | 0 - 127 128 - 255 | RED LASER LASER OFF LASER ON |
| 6 | 0 - 127 128 - 255 | GREEN LASER LASER OFF LASER ON |
| 7 | 0 - 9 10 - 120 121 - 134 135 - 245 246 - 255 | LASER ROTATION NO ROTATION CLOCKWISE ROTATION FAST-SLOW NO ROTATION COUNTER-CLOCKWISE ROTATION SLOW-FAST NO ROTATION |

| Fusion FX Bar 5 UC3 Control | | |
|-----------------------------|---|--------------------------|
| Stand By | Blackout the unit | |
| Function | 1. White LED Strobe 2. Moonflower Strobe | Select Shows 1~16 |
| Mode | Sound (LED OFF) | Speed (LED ON) |